

SpeakerCraft®



SonicAir 2.1

Custom installation is all about finding ways to deliver entertainment in and throughout the home while making the technology itself virtually invisible. At times this can be an overwhelming challenge due to construction methods and architectural designs. Wires simply can't be discreetly run in vaulted ceilings and under concrete slabs without extreme cost and inconvenience to the customer. Fortunately wireless technology has given us additional options that were simply not available only a few years ago.

The new SA 2.1 is a tremendous solution for transmitting audio signals through a home with very little time and effort. A two piece system made up of both a transmitter and a receiver, the SA 2.1 is perfect for sending rear channel information to the back of the room, a subwoofer signal to a corner location or even a second zone's audio to one or more bedrooms.

The transmitter, placed near the source equipment, has both speaker level and line level inputs for flexibility. The receiver can be placed up to 100 feet from the transmitter and offers a line level mono (summed) output to feed a powered sub, as well as a fifty-watt amplifier to power the remote speakers. There is also a local input on the front of the receiver to allow for connection to an iPod® or other local source. Adjustable EQ, via a series of dipswitches, is also standard.

If you are looking for a way to wirelessly transmit audio to a hard to reach location in the home, the SA 2.1 will be a lifesaver.



SonicAir 2.1

- Wireless Transmitter and Receiver
- Amplifier Power Output: 50 Watts x 2 Channels
- Receiver: Output - Speaker Level x 2 Sets Binding Posts, Subwoofer Mini Jack
Input - Auxiliary Mini Jack
- Transmitter: Input - Pre-Amp Inputs, Speaker Level x 2 Set Binding Posts
- Operating Range: 100ft.
- Frequency Response: 20Hz - 20kHz
- RF Frequency: 2.4GHz
- Wall Mount Included
- Universal Power Supply
- Includes Remote Control
- Transmitter Dimensions: (H x W x D) 1 $\frac{3}{16}$ " x 6 $\frac{1}{8}$ " x 4 $\frac{3}{4}$ " (33 mm x 156 mm x 121 mm)
- Receiver Dimensions: (H x W x D) 1 $\frac{1}{4}$ " x 6" x 4 $\frac{1}{8}$ " (32 mm x 152 mm x 105 mm)



The SonicAir offers an elegant wireless solution for simple transmission of stereo audio signals up to 100 feet in the home or office. This two-piece system begins with a transmitter at the head end with either line level or speaker level inputs.

Another option is to use the system to connect a subwoofer to the main system. This can be done by simply connecting the LFE line level output to one side of the stereo pair or by using the summed output from the stereo inputs. The receiver is attached to the back of the subwoofer with an optional mounting bracket. Either way, the result is a wireless subwoofer that can be placed anywhere in the room.

* SonicAir come with Limited TWO Year Warranty

* As we incorporate design improvements, specifications may change without notice



940 Columbia Ave., Riverside CA 92507 • USA (800) 448 0976 Fax (951) 787 8747 International +1 951 787 0543 • www.speakercraft.com